


Leda 3-CCT LED Batten



Tri-Colour



Our Leda range of contemporary LED batten fittings, featuring quality LED boards, make an ideal replacement for traditional fluorescent battens. They are suitable for all kinds of commercial and retail applications, giving an aesthetically pleasing, energy saving solution and now feature 3-CCT capability to switch between 3000K, 4000K and 6000K.




- 3-CCT Switch - switch between 3000K/4000K/6000K
- High Quality integrated LED Chips and driver
- Hinged opening for easy installation
- Steel housing and Polycarbonate covers
- Compatible with PIR or microwave sensors
- Dimmable & Emergency versions available
- 5-Year Warranty

Datasheet:

Leda 3-CCT LED Batten

Code	Description	Wattage	Lumens	Dimensions (mm)
500001 (Standard) 500041 (Emergency)	4ft Single 20w Leda LED Batten Fitting	20w	(3000K/4000K /6000K) 2500 2700 2600	1172x62x74
500004 (Standard) 500044 (Emergency)	4ft Twin 38w Leda LED Batten Fitting	38w	4750 5130 4940	1172x62x74
500002 (Standard) 500042 (Emergency)	5ft Single 32w Leda LED Batten Fitting	32w	4000 4320 4160	1462x62x74
500005 (Standard) 500045 (Emergency)	5ft Twin 52w Leda LED Batten Fitting	52w	6500 7020 6760	1462x62x74
500003 (Standard) 500043 (Emergency)	6ft Single 40w Leda LED Batten Fitting	40w	5000 5400 5200	1732x62x74
500006 (Standard) 500046 (Emergency)	6ft Twin 60w Leda LED Batten Fitting	60w	7500 8100 7800	1732x62x74

*Add the following suffices to your code (e.g. /DSI for DSI Dimming, /DALI for DALI Dimming)

Dimming Options 	Emergency Options 	Sensor Options 
DSI - Digital Signal Dimmable	EM3 - Emergency	PIR - PIR Sensor
DALI - Dali Addressable Dimmable	EM3-ST - Emergency Self Test	PIR- 20M- PIR Sensor 20 metre
AD - Analogue 1-10v Dimmable	EM3-DA - Emergency DALI addressable	PIR-DIM - PIR Sensor with Daylight Dimming Options
	EM3- CB* - Emergency Central Battery *please advise voltage	PIR-DIM-20M - PIR Sensor 20 metre with Daylight Dimming Options